

PMi 6500 HAU



FEATURES


- Inverter technology: stable power for safe operation of sensitive electronics.
- OHV engine provides consistent power for multiple applications.
- Low-oil level shutdown automatically safeguards engine from damage.
- Economy mode automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction.
- Lightweight and compact.
- Wheel kit integrated for easy transportation
- Fuel gauge allows user to track gasoline levels

- ATS connector
- Remote control
- 2 wire start



PERFORMANCE

Frequency	Hz	50
Voltage	V	230
Phase		1
Max Power	watt	6500
Rated Power	watt	6000



Engine		
Brand	Pramac	
Type	OHV	
Exhaust emission level	Stage V	
Operating Speed Nominal	rpm	Variable
Fuel	Petrol	
Starting Systems	Electric (+Recoil)	
Oil capacity	l	0.85
Low Oil Shutdown	✓	

Alternator Specifications		
Voltage regulation system	Inverter	

Dimensional data		
Length	(L) mm	625
Width	(W) mm	448
Height	(H) mm	560
Dry weight	kg	52
Carton box dimension LxWxH	mm	680x500x610

Autonomy		
Fuel tank capacity	l	14
Fuel consumption 50%	l/h	2.1
Running time 50% (Eco Mode)	h	6.6

Noise level		
Guaranteed noise level (LWA)	dB(A)	96
Noise pressure level @ 7 m	dB(A)	68

GENSET CONTROL

COMMANDS:

- Electric start button
- Smart throttle: Economy mode automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction
- ATS connector / 2 wire start / Remote control

INSTRUMENTATION:

- Voltage (V), Frequency (Hz) , Running time (h)
- Oil alarming / output power / Fuel level indicator on the tank
- Ground pin
- 12V battery maintainer holder

PROTECTIONS

- Overcurrent / Overspeed / High temperature / AC thermal circuit breaker / DC circuit breaker

SOCKET TYPE

AS/NZS 3123 32A 230 V (IP66)	1
AS/NZS 3112 15A 230 V (IP66)	1



ACCESSORIES CONTROL PANEL

ATS - Automatic Transfer Switch for an optimal home safety

With the Pramac Automatic Transfer Switch, you can easily connect your generator to the power grid and continue to supply your domestic appliances in case of a power outage.

Equipment:

- Control unit
- Contactor with interblock
- Battery charged
- 5 meters control wiring (with connector)
- emergency stop button

Status indicators:


- House Grid (lamp)
- Generator (lamp)
- Auto (lamp)
- Battery (lamp)
- Failure (lamp)

It is strongly recommended that your Home Standby equipment be installed by a professional.



DIMENSIONS PANEL

Width	(W) mm	250
Height	(H) mm	389
Depth	(D) mm	165
Weight	kg	6



The information is aligned with the Data file at the time of download.
Printed on 22/07/2026 (ID 207942)

©2026 | PR Industrial S.r.L. – Loc. Il Piano – 53031 Casole d'Elsa (SI) – ITALY. Company subject to the management and coordination of Generac Power Systems Inc. | All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice

