

PMi 4500+HAU



Pramac PMi series inverter: optimal solution to combine silent operation with less fuel consumption and tension stability; the inverters Pramac stabilize the output tension and supply power for all kinds of equipment. They guarantee maximum efficiency: adjusting the speed according to the required load, our inverters reduce the average fuel consumption.

FEATURES

- Inverter technology: stable power for safe operation of sensitive electronics.
- OHV engine provides consistent power for multiple applications.
- Low-oil level shutdown automatically safeguards engine from damage.
- Economy mode automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction.
- ATS connector
- Remote control
- 2 wire start
- Lightweight and compact.
- Wheel kit integrated for easy transportation
- Fuel gauge allows user to track gasoline levels



PERFORMANCE

Frequency	Hz	50
Voltage	V	230
Phase		1
Max Power	watt	4200
Rated Power	watt	3800



Engine		
Brand	Pramac	
Type	OHV	
Exhaust emission level	Stage V	
Operating Speed Nominal	rpm	Variable
Fuel	Petrol	
Starting Systems	Electric (+Recoil)	
Oil capacity	l	0.78
Low Oil Shutdown	✓	

Alternator		
Voltage regulation system	Inverter	

Dimensional data		
Length	(L) mm	578
Width	(W) mm	422
Height	(H) mm	500
Dry weight	kg	42.5
Carton box dimension LxWxH	mm	660x505x580

Autonomy		
Fuel tank capacity		12
Fuel consumption 50%	l/h	1.2
Running time 50% (Eco Mode)	h	9.7

Noise level		
Guaranteed noise level (LWA)	dB(A)	93
Noise pressure level @ 7 m	dB(A)	68

COMMANDS:

- Electric start button
- Smart throttle: Economy mode automatically adjusts the engine speed to the optimum level to provide excellent fuel economy and noise reduction
- ATS connector / 2 wire start / Remote control

INSTRUMENTATION:

- Voltage (V), Frequency (Hz) , Running time (h)
- Oil alarming / output power
- Fuel level indicator on the tank
- 12V battery maintainer holder

PROTECTIONS

- Overcurrent / Overspeed / High temperature / AC thermal circuit breaker / DC circuit breaker

OUTPUT:

- DC12V 6A

SOCKET TYPE

AS/NZS 3112 15A 250V	2
----------------------	---

The information is aligned with the Data file at the time of download.
Printed on 21/08/2025 (ID 195853)

©2024 | PR Industrial S.r.L unipersonale – Loc. Il Piano – 53031 Casole d'Elsa (SI) – ITALY. Company subject to the management and coordination of Generac Power Systems Inc. All rights reserved
| Image shown may not reflect actual package. Specifications subject to change without notice



Two Great Stores to choose from...

7 Cemetery Rd,
Mackay QLD 4740
Phone 07 4957 6123

Unit 16, 547 Woolcock St,
Mt Louisa, Townsville QLD 4814
Phone 07 4774 7344