

BLUETTI AC180T Portable Power Station | 1,800W 1,433.6Wh

- 1,800W AC Output / 2,700W Power Lifting Mode
- Capacity: 1,433Wh (2pcs x B70, 716Wh)
- Swappable Battery Design for Easy handling
- The power station of SwapSolar Ecosystem
- 0-80% Recharging in 45Mins with 1,440W AC Input
- 7 Output Ports for Multiple Devices
- Smart Control & Monitor with BLUETTI App
- Eco-friendly/Clean/Quiet/Cost-effective



Specifications

BATTERY INFO

Capacity:	1433.6Wh, 2pcs x (716.8Wh/28Ah)
Type:	LiFePO ₄ (Lithium Iron Phosphate)
Life Cycles:	3,500+ Cycles to 80% Original Capacity
Shelf-life:	Recharge to 40%-60% Every 3-6 Months
Management System:	BLUETOPUS AI-BMS

INPUT

AC Input:	1,440W Max (w/2 batteries)
Solar Input:	12V - 60V, 500W Max.
Car Input:	12/24V from Cigarette Lighter Port

RECHARGE TIME

AC Charging Time (1,440 Max):	70 Minutes (w/1 battery) 1.5 Hours (w/2 batteries)
Solar Charging Time (500W):	≈2.5 Hours (With prime sunshine, ideal orientation and low temperature)
12V/24V Car Outlet (100W/200W):	14-14.5 Hours / 7-7.5 Hours

GENERAL

Hot Swappable:	Yes
Pass-through Charging:	Yes
Weight:	About 26.5kg /58.4lbs (w/ 2 batteries)
Dimensions (LxWxD):	390 x280 x395mm / 15.4 x11.0 x15.6in
Charging Temperature:	32°F-104°F / 0°C-40°C
Discharging Temperature:	-4°F-104°F (86°F-104°F: 1.500W Max.) -20°C-40°C (30°C-40°C: 1.500W Max.)
Storage Temperature:	-4°F -104°F / -20°C-40°C
Certifications:	UKCA, PSE, TELEC, RCM, CE, CA65, UL Standard
Warranty:	5 Years



Two Great Stores to choose from...

7 Cemetery Rd,
Mackay QLD 4740

Phone 07 4957 6123

Unit 16, 547 Woolcock St,
Mt Louisa, Townsville QLD 4814

Phone 07 4774 7344

In The Box



Solar Charging Cable



Car Charging Cable



AC Charging Cable



Grounding Screw



User Manual



Warranty Card



AC180T Power Station