

PS MANUAL

# **BCS-BATTERY CHARGERS**

1.0 <u>Model</u> BCS-A1220

2.0 <u>Description</u>

12 Volt 20Amp SmartCharger Battery Charger









#### PS MANUAL

#### 3.0 <u>Features</u>

- Fully Automatic, Fast and Safe.
- Overcharging Protection.
- Short Circuit Protection
- High Efficiency
- Three stage Charging indicator LED's
- Eliminates Sulphation
- Compact and Lightweight
- Leads and Battery Clamps
- Australian Electrical Standard & EMC Compliant
- Available with Optional plug to suit Mobility Scooters, wheel chairs etc

#### 4.0 Physical and Dimensional Properties

- Each unit weighs approximately 1.2 Kg
- Width 118 mm
- Length 190 mm
- Height 58 mm
- Carton Dimensions: 280 x 230 x 100
- Colour: Red

### 5.0 <u>Performance</u>

- Voltage 200-240 Volt
- Frequency 47-63 Hz
- Output Current: 20 Amps
- Boost Voltage 14.4 Volts
- Float Voltage 13.7 Volts
- Wattage: 294W
- Battery size Ahr 60 Ahr 300 Ahr

#### 6.0 <u>Uses</u>

- SmartCharger Battery Charger.
- Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances, Golf Carts, Solar, Deep Cycle, UPS Standby.

## 7.0 <u>Documentation</u>

- Bar Code Number: 9346080001447
- Product Specification Manual PS 157
- Work Instruction Manual WI 157
- Product Costing Manual PC 157



